

# Camera/Recorder Compatibility

	Function	WV-X8570N/S8530N	WV-X6531LN/S6532LN	WV-X6531N/X6531NS X6511N	WV-S6530N	WV-S6131/S6111/S6130	WV-X4171/X4571L/X4571LM	WV-X4170	WV-S4550L/S4550LM	WV-S4150	WV-S1132/S1131	WV-S1550L	WV-S1531LN/S1531LTN S1531LNS	WV-S2131L/S2130
WJ-NX400 (V3.00) *20	MJPEG	no	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	H.265	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	Audio	yes (for X8570N) *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23
	PTZ	-	yes	yes	yes	yes	yes	-	-	-	-	-	-	-
Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
WJ-NX300 (V3.00) *20	MJPEG	no	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	H.265	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	Audio	yes (for X8570N) *23	yes *23	yes *23	yes *23	yes *23	yes *23	-	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23
	PTZ	-	yes	yes	yes	yes	yes	-	-	-	-	-	-	-
Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
WJ-NX200 (V3.00) *20	MJPEG	no	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	H.265	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	Audio	yes (for X8570N) *23	yes *23	yes *23	yes *23	yes *23	yes *23	-	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23
	PTZ	-	yes	yes	yes	yes	yes	-	-	-	-	-	-	-
Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
WJ-NV300 (V2.30) *14	MJPEG	-	[X6531/S6530]	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	-	[X6531/S6530]	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	H.265	-	no	no	no	no	-	-	-	no	no	no	no	
	Audio *8	-	[X6531/S6530]	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	PTZ	-	[X6531/S6530]	yes	yes	yes	yes	-	-	-	-	-	-	
Motion detection (VMD)	-	[X6531/S6530]	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes		
WJ-NV200 (V2.60) *14 (Discontinued model)	MJPEG	-	[SW598]	[SW598]	[SW598]	[SW598]	-	-	-	-	[SPN631]	-	[SPW631]	[SFN631]
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	-	[SW598] *21*22	[SW598] *21*22	[SW598] *21*22	[SW598] *21*22	-	-	-	-	[SPN631] *22	-	[SPW631] *22	[SFN631] *22
	H.265	-	no	no	no	no	-	-	-	-	no	no	no	
	Audio *8	-	[SW598]	[SW598]	[SW598]	[SW598]	-	-	-	-	[SPN631]	-	[SPW631]	[SFN631]
	PTZ	-	[SW598]	[SW598]	[SW598]	[SW598]	-	-	-	-	-	-	-	
Motion detection (VMD)	-	[SW598]	[SW598]	[SW598]	[SW598]	-	-	-	-	[SPN631]	-	[SPW631]	[SFN631]	
WJ-ND400K (V6.10) *14	MJPEG	-	[X6531/S6530]	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	-	[X6531/S6530]	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	H.265	-	no	no	no	no	-	-	-	no	no	no	no	
	Audio *8	-	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	PTZ	-	yes	yes	yes	yes	yes	-	-	-	-	-	-	
Motion detection (VMD)	-	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes		
WJ-ND300A (V5.20) *4, *14 (Discontinued model)	MJPEG	-	[SC385]*2	[SC385]*2	[SC385]*2	[SC385]*2	-	-	-	-	[SP305] *2	-	[SP305] *2	[SP305] *2
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	-	-	-	-	-	-	-	-	-	-	-	-	
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	
	Audio	-	-	-	-	-	-	-	-	-	-	-	-	
	PTZ	-	[SC385]	[SC385]	[SC385]	[SC385]	-	-	-	-	-	-	-	
Motion detection (VMD)	-	[SC385]	[SC385]	[SC385]	[SC385]	-	-	-	-	-	-	-		
WJ-ND200 (V3.35) *4, *14 (Discontinued model)	MJPEG	-	[SC385]*2	[SC385]*2	[SC385]*2	[SC385]*2	-	-	-	-	[SP305] *2	-	[SP305] *2	[SP305] *2
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	-	-	-	-	-	-	-	-	-	-	-	-	
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	
	Audio *8*11	-	[SC385]	[SC385]	[SC385]	[SC385]	-	-	-	-	[SP305]	-	[SP305]	[SP305]
	PTZ	-	[SC385]	[SC385]	[SC385]	[SC385]	-	-	-	-	-	-	-	
Motion detection (VMD)	-	-	-	-	-	-	-	-	-	-	-	-		

[substitute model] : Register as a substitute model.  
 \*1 : Only for remote PTZ cameras.  
 \*2 : Support less than 1920x1080, including 1600x1200. 1920x1080 and 1600x1200 are not supported SD memory card backup and can be set the image quality:5-9 and the frame rate:up to 5fps.  
 \*3 : Each recorder supports only wireline connection.  
 \*4 : Displaying 16:9 is not supported on a NDR browser.  
 \*5 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.  
 \*6 : Supported G.726 and 32kbps.  
 \*7 : This function is supported only when playing back.  
 \*8 : Supported up to 30 ips  
 \*9 : When using WV-SFV481/WV-SFN480 with WJ-NV200, recording stops for about 10 seconds at the time of a screen change in a main monitor.  
 \*10 : Streams of H.264(3) and H.264(4) are not supported  
 \*11 : When using over 6Mbps for bitrate, please use the "4K resolution" mode. SFV781L, SPV781L, SFV481, SFN480 support will be only 1-8ch.  
 \*12 : The fish-eye dewarp function on the main monitor is supported.  
 \*13 : The fish-eye dewarp function is supported by using the management software(WV-ASM200, WV-ASC970).  
 \*14 : Supported maximum bitrate is 14Mbps.  
 \*15 : 3rd stream and 4th stream of H.265 are supported, only when using H.265 cameras  
 \*16 : Support less than 1280x720 for WV-X6511N  
 \*17 : Transmission format must be switched from H.265(Factory default) to H.264 by connecting from web browser  
 \*18 : Supported G.726/32kbps and AAC-LC/64kbps  
 \*19 : Supported image capture sites are 4KUHD(3840x2160), WQHD(2560x1440), FHD(1920x1080) and HD(1280x720).  
 \*20 : Supported image capture sites are 4KUHD(3840x2160), WQHD(2560x1440), FHD(1920x1080) and HD(1280x720).

# Camera/Recorder Compatibility

	Function	WW-S2231	WW-S2550L/S2250L	WW-S2531LN/S2531LTN	WW-S1112/S1111	WW-S1511LN	WW-S2111L/S21110	WW-S2311	WW-S2511LN	WW-S3131L	WW-S3111L	WW-S3531L	WW-S3511L	WW-S3532LM/ S3512LM	
WJ-NX400 (V3.00) *20	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-	
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-	
	H.265	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-	
	Audio	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	-
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-
WJ-NX300 (V3.00) *20	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-	
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-	
	H.265	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-	
	Audio	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	-
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-
WJ-NX200 (V3.00) *20	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-	
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-	
	H.265	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-	
	Audio	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	yes *23	-
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-
WJ-NV300 (V2.30) *14	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-	
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-	
	H.265	no	no	no	no	no	no	no	no	no	no	no	no	-	
	Audio *8	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-
WJ-NV200 (V2.60) *14 (Discontinued model)	MJPEG	[SFV631]	-	[SFV631]	[SPN631]	[SPW631]	[SFN631]	[SFV631]	[SFV631]	[SFN130]	[SFN110]	[SFV130]	[SFV110]	-	
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	[SFV631]*22	-	[SFV631]*22	[SPN631]*22	[SPW631]*22	[SFN631]*22	[SFV631]*22	[SFV631]*22	[SFN130]*22	[SFN110]*22	[SFV130]*22	[SFV110]*22	-	
	H.265	no	no	no	no	no	no	no	no	no	no	no	no	-	
	Audio *8	[SFV631]	-	[SFV631]	[SPN631]	[SPW631]	[SFN631]	[SFV631]	[SFV631]	[SFN130]	[SFN110]	[SFV130]	[SFV110]	-	
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	
	Motion detection (VMD)	[SFV631]	-	[SFV631]	[SPN631]	[SPW631]	[SFN631]	[SFV631]	[SFV631]	[SFN130]	[SFN110]	[SFV130]	[SFV110]	-	
WJ-ND400K (V6.10) *14	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-	
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-	
	H.265	no	no	no	no	no	no	no	no	no	no	no	no	-	
	Audio *8	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	
	Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
WJ-ND300A (V5.20) *4, *14 (Discontinued model)	MJPEG	[SP305]*2	-	[SP305]*2	[SP305]*2	[SP305]*2	[SP305]*2	[SP305]*2	[SP305]*2	[SP305]*2	[SP305]*2	[SP305]*2	[SP305]*2	-	
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	
	Audio	-	-	-	-	-	-	-	-	-	-	-	-	-	
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	
	Motion detection (VMD)	-	-	-	-	-	-	-	-	-	-	-	-	-	
WJ-ND200 (V3.35) *4, *14 (Discontinued model)	MJPEG	[SP305]*2	-	[SP305]*2	[SP305]*2	[SP305]*2	[SP305]*2	[SP305]*2	[SP305]*2	[SP305]*2	[SP305]*2	[SP305]*2	[SP305]*2	-	
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	
	Audio *8 *11	[SP305]	-	[SP305]	[SP305]	[SP305]	[SP305]	[SP305]	[SP305]	[SP305]	[SP305]	[SP305]	[SP305]	-	
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	
	Motion detection (VMD)	-	-	-	-	-	-	-	-	-	-	-	-	-	

[substitute model] : Register as a substitute model.  
 \*1 : Only for remote PTZ cameras.  
 \*2 : Support less than 1920x1080 ,including 1600x1200. 1920x1080 and 1600x1200 are not supported SD memory card backup and can be set the image quality:5-9 and the frame rate:up to 5fps.  
 \*3 : Each recorder supports only wireline connection.  
 \*4 : Displaying 16:9 is not supported on a NDR browser.  
 \*7 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.  
 \*8 : Supported G.726 and 32kbps.  
 \*11 : This function is supported only when playing back.  
 \*12 : Supported up to 30 fps  
 \*13 : When using WW-SFV481/WW-SFN480 with WJ-NV200, recording stops for about 10 seconds at the time of a screen change in a main monitor.  
 \*14 : Streams of H.264(3) and H.264(4) are not supported.  
 \*15 : When using over 6Mbps for bitrate, please use the "4K resolution" mode. SFV781L, SPV781L, SFV481, SFN480 support will be only 1-8ch.  
 \*17 : The fish-eye dewarp function on the main monitor is supported.  
 \*18 : The fish-eye dewarp function is supported by using the management software(WW-ASM200, WW-ASC970).  
 \*19 : Supported maximum bitrate is 14Mbps.  
 \*20 : 3rd stream and 4th stream of H.264 are supported, only when using H.265 cameras  
 \*21 : Support less than 1280x720 for WW-X6511N  
 \*22 : Transmission format must be switched from H.265(Factory default) to H.264 by connecting from web browser  
 \*23 : Supported G.726/32kbps and AAC-LC/64kbps  
 \*24 : Supported image capture sites are 4KUHD(3840x2160), WQHD(2560x1440), FHD(1920x1080) and HD(1280x720).

# Camera/Recorder Compatibility

	Function	WW-67670L/68270L/61570L	WW-SFV781L/SPV781L	WW-SUD638	WW-SPN611/SPN631	WW-SPW631LT/SPW631L	WW-SFN611L/SFN631L/SFR611L/SFR631L/SFV611L/SFV631L/SFV631LT	WW-SPW611L/SPW611	WW-SPN531/SPN531A	WW-SPW532L	WW-SPW531AL	WW-SFN531/SFR531/SFV531	WW-SW598/SW598A/SC588/SC588A	WW-SW559/SF549/SF539	
WJ-NX400 (V3.00) *20	MJPEG	no	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	yes*19	yes*19	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	
	Audio	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*8	yes*8
	PTZ	-	-	yes	-	-	-	-	-	-	-	-	-	yes	-
Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
WJ-NX300 (V3.00) *20	MJPEG	no	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	yes*19	yes*19	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	
	Audio	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*8	yes*8	
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	
Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes		
WJ-NX200 (V3.00) *20	MJPEG	no	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	yes*19	yes*19	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	
	Audio	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*23	yes*8	yes*8	
	PTZ	-	-	yes	-	-	-	-	-	-	-	-	yes	-	
Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes		
WJ-NV300 (V2.30) *14	MJPEG	-	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	[SFV781/SPV781]*22, *24	-	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	H.265	no	-	-	-	-	-	-	-	-	-	-	-	-	
	Audio *8	[SFV781/SPV781]	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	PTZ	-	-	yes	-	-	-	-	-	-	-	-	-	-	
Motion detection (VMD)	[SFV781/SPV781]	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes		
WJ-NV200 (V2.60) *14 (Discontinued model)	MJPEG	-	-	[SW598]	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	-	-	[SW598]	yes*12	yes*12	yes*12	yes*12	yes*12	yes*12	yes*12	yes*12	yes	yes	
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	
	Audio *8	-	-	[SW598]	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	PTZ	-	-	[SW598]	-	-	-	-	-	-	-	-	-	yes	
Motion detection (VMD)	-	-	[SW598]	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes		
WJ-ND400K (V6.10) *14	MJPEG	[SFV781/SPV781]	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	[SFV781/SPV781]*15,*19	yes*15,*19	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	H.265	no	-	-	-	-	-	-	-	-	-	-	-	-	
	Audio *8	[SFV781/SPV781]	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	
	PTZ	-	-	yes	-	-	-	-	-	-	-	-	-	yes	
Motion detection (VMD)	[SFV781/SPV781]	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes		
WJ-ND300A (V5.20) *4, *14 (Discontinued model)	MJPEG	-	-	[SC385]*2	[SP305]*2	[SP305]*2	[SF335]*2	[SP305]	[SP305]*2	[SP305]*2	[SP305]*2	[SF335]*2	[SC385]*2	[SF335]*2	
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	
	Audio	-	-	-	-	-	-	-	-	-	-	-	-	-	
	PTZ	-	-	[SC385]	-	-	-	-	-	-	-	-	[SC385]	-	
Motion detection (VMD)	-	-	-	-	-	-	-	-	-	-	-	-	-		
WJ-ND200 (V3.35) *4, *14 (Discontinued model)	MJPEG	-	-	[SC385]*2	[SP305]*2	[SP305]*2	[SF335]*2	[SP305]	[SP305]*2	[SP305]*2	[SP305]*2	[SF335]*2	[SC385]*2	[SF335]*2	
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.264	-	-	-	-	-	-	-	-	-	-	-	-	-	
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	
	Audio *8*11	-	-	[SC385]	[SP305]	[SP305]	[SF335]	[SP305]	[SP305]	[SP305]	[SP305]	[SF335]	[SC385]	[SF335]	
	PTZ	-	-	[SC385]	-	-	-	-	-	-	-	-	[SC385]	-	
Motion detection (VMD)	-	-	-	-	-	-	-	-	-	-	-	-	-		

[substitute model] : Register as a substitute model.  
 \*1 : Only for remote PTZ cameras.  
 \*2 : Support less than 1920x1080 ,including 1600x1200. 1920x1080 and 1600x1200 are not supported SD memory card backup and can be set the image quality:5-9 and the frame rate:up to 5fps.  
 \*3 : Each recorder supports only wireline connection.  
 \*4 : Displaying 16:9 is not supported on a NDR browser.  
 \*7 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.  
 \*8 : Supported G.726 and 32kbps.  
 \*11 : This function is supported only when playing back.  
 \*12 : Supported up to 30 fps  
 \*13 : When using WW-SFV481/WW-SFN480 with WJ-NV200, recording stops for about 10 seconds at the time of a screen change in a main monitor.  
 \*14 : Streams of H.264(3) and H.264(4) are not supported  
 \*15 : When using over 6Mbps for bitrate, please use the "4K resolution" mode. SFV781L, SPV781L, SFV481, SFN480 support will be only 1-8ch.  
 \*17 : The fish-eye dewarp function on the main monitor is supported.  
 \*18 : The fish-eye dewarp function is supported by using the management software(WW-ASM200, WW-ASC970).  
 \*19 : Supported maximum bitrate is 14Mbps.  
 \*20 : 3rd stream and 4th stream of H.264 are supported, only when using H.265 cameras  
 \*21 : Support less than 1280x720 for WW-X6511N  
 \*22 : Transmission format must be switched from H.265(Factory default) to H.264 by connecting from web browser  
 \*23 : Supported G.726/32kbps and AAC-LC/64kbps  
 \*24 : Supported image capture sites are 4KUHD(3840x2160), WQHD(2560x1440), FHD(1920x1080) and HD(1280x720).

# Camera/Recorder Compatibility

	Function	WV-SW558/SF548/SF538	WV-SP509	WV-SP508	WV-NW50 2S/NP502	WV-SFV481/SFN480 *7	WV-SW458/SW458MA/SF438/SF448E *7	WV-SFV130(M)/SFV110(M)	WV-SFN130/SFN110	WV-SW158/SF138	WV-SW155/SW155MA/SW152/SW115	WV-SF135/SF132	WV-SP105/SP102	WV-SW175/SW172/ST165/ST162
WJ-NX400 (V3.00) *20	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	-	yes	-	yes	yes *17,*18,*19	yes *17,*18	yes	yes	yes	-	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio	-	yes *8	-	yes *8	yes *23	yes *8	yes *23	yes *23	yes *8	-	-	-	yes *8
	PTZ	-	-	-	-	-	yes	-	-	-	-	-	-	-
Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
WJ-NX300 (V3.00) *20	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes *17,*18,*19	yes *17,*18	yes	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio	-	yes *8	-	yes *8	yes *23	yes *8	yes *23	yes *23	yes *8	-	-	-	yes *8
	PTZ	-	-	-	-	-	yes	-	-	-	-	-	-	-
Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
WJ-NX200 (V3.00) *20	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes *17,*18,*19	yes *17,*18	yes	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio	-	yes *8	-	yes *8	yes *23	yes *8	yes *23	yes *23	yes *8	-	-	-	yes *8
	PTZ	-	-	-	-	-	yes	-	-	-	-	-	-	-
Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
WJ-NV300 (V2.30) *14	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes *17,*18,*19	yes *17,*18	yes	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *8	-	yes	-	yes	yes	yes	yes	yes	yes	-	-	-	yes
	PTZ	-	-	-	-	-	yes	-	-	-	-	-	-	-
Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
WJ-NV200 (V2.60) *14 (Discontinued model)	MJPEG	yes	yes	yes	yes	no *13	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	no *13	yes	yes	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *8	-	yes	-	yes	no *13	yes	yes	yes	yes	-	-	-	yes
	PTZ	-	-	-	-	-	yes	-	-	-	-	-	-	-
Motion detection (VMD)	yes	yes	yes	yes	no *13	yes	yes	yes	yes	yes	yes	yes	yes	yes
WJ-ND400K (V6.10) *14	MJPEG	yes	yes	yes	yes	yes *15	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes *15,*18,*19	yes *18	yes	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *8	-	yes	-	yes	yes *15	yes	yes	yes	yes	-	-	-	yes
	PTZ	-	-	-	-	yes *15	yes	-	-	-	-	-	-	-
Motion detection (VMD)	yes	yes	yes	yes	yes *15	yes	yes	yes	yes	yes	yes	yes	yes	yes
WJ-ND300A (V5.20) *4, *14 (Discontinued model)	MJPEG	[SP102] *2	[SP305] *2	[SP102] *2	yes *2	-	-	[SF335] *2	[SF335] *2	[SF335] *2	[SF335]	[SP102]	yes	[SC385]
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	-	-	-	yes	-	-	-	-	-	[SF335]	[SF335]	yes	[SC385]
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio	-	-	-	-	-	-	-	-	-	-	-	-	-
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	[SC385]
Motion detection (VMD)	-	-	-	-	-	-	-	-	-	-	-	-	-	
WJ-ND200 (V3.35) *4, *14 (Discontinued model)	MJPEG	[SF335] *2	[SP305] *2	[SP305] *2	yes *2	-	-	[SF335] *2	[SF335] *2	[SF335] *2	[SF335]	[SF335]	yes	[SC385]
	MPEG4	-	-	-	yes	-	-	-	-	-	-	-	-	-
	H.264	-	-	-	yes	-	-	-	-	-	[SF335]	[SF335]	yes	[SC385]
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *8 *11	-	[SP305]	-	yes	-	-	[SF335]	[SF335]	[SF335]	-	-	-	[SC385]
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	[SC385]
Motion detection (VMD)	-	-	-	-	-	-	-	-	-	-	-	-	-	

[substitute model] : Register as a substitute model.  
 \*1 : Only for remote PTZ cameras.  
 \*2 : Support less than 1920x1080 ,including 1600x1200. 1920x1080 and 1600x1200 are not supported SD memory card backup and can be set the image quality:5-9 and the frame rate:upto 5fps.  
 \*3 : Each recorder supports only wireline connection.  
 \*4 : Displaying 16:9 is not supported on a NDR browser.  
 \*7 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.  
 \*8 : Supported G.726 and 32kbps.  
 \*11 : This function is supported only when playing back.  
 \*12 : Supported up to 30 fps  
 \*13 : When using WV-SFV481/WV-SFN480 with WJ-NV200, recording stops for about 10 seconds at the time of a screen change in a main monitor.  
 \*14 : Streams of H.264(3) and H.264(4) are not supported  
 \*15 : When using over 6Mbps for bitrate, please use the "4K resolution" mode. SFV781L, SPV781L, SFV481, SFN480 support will be only 1-8ch.  
 \*17 : The fish-eye dewarp function on the main monitor is supported.  
 \*18 : The fish-eye dewarp function is supported by using the management software(WV-ASM200, WV-ASC970).  
 \*19 : Supported maximum bitrate is 14Mbps.  
 \*20 : 3rd stream and 4th stream of H.264 are supported, only when using H.265 cameras  
 \*21 : Support less than 1280x720 for WV-X6511N  
 \*22 : Transmission format must be switched from H.265(Factory default) to H.264 by connecting from web browser  
 \*23 : Supported G.726/32kbps and AAC-LC/64kbps  
 \*24 : Supported image capture sites are 4KUHD(3840x2160), WQHD(2560x1440), FHD(1920x1080) and HD(1280x720).

	Function	WV-SW174W *3	BB-HCM7 series	BB-HCM5 series	WJ-GXE500	WJ-GXE100
WJ-NX400 (V3.00) *20	MJPEG	yes	yes	yes	yes	yes
	MPEG4	-	no	-	no	-
	H.264	yes	yes	-	yes	yes
	H.265	-	-	-	-	-
	Audio *8	yes *8	yes *8	-	yes (ch1) *8	-
	PTZ	yes	yes *1	yes *1	yes	yes
	Motion detection (VMD)	yes	-	-	yes	yes
WJ-NX300 (V3.00) *20	MJPEG	yes	yes	yes	yes	yes
	MPEG4	-	no	-	no	-
	H.264	yes	yes	-	yes	yes
	H.265	-	-	-	-	-
	Audio	yes *8	yes *8	-	yes (ch1) *8	-
	PTZ	yes	yes *1	yes *1	yes	yes
	Motion detection (VMD)	yes	-	-	yes	yes
WJ-NX200 (V3.00) *20	MJPEG	yes	yes	yes	yes	yes
	MPEG4	-	no	-	no	-
	H.264	yes	yes	-	yes	yes
	H.265	-	-	-	-	-
	Audio	yes *8	yes *8	-	yes (ch1) *8	-
	PTZ	yes	yes *1	yes *1	yes	yes
	Motion detection (VMD)	yes	-	-	yes	yes
WJ-NV300 (V2.30) *14	MJPEG	yes	yes	yes	yes	yes
	MPEG4	-	no	-	no	-
	H.264	yes	yes	-	yes	yes
	H.265	-	-	-	-	-
	Audio *8	yes	yes	-	yes (ch1)	-
	PTZ	yes	yes *1	yes *1	yes	yes
	Motion detection (VMD)	yes	-	-	yes	yes
WJ-NV200 (V2.60) *14 (Discontinued model)	MJPEG	yes	yes	yes	yes	yes
	MPEG4	-	yes	-	yes	-
	H.264	yes	yes	-	yes	yes
	H.265	-	-	-	-	-
	Audio *8	yes	yes	-	yes (ch1)	-
	PTZ	yes	yes *1	yes *1	yes	yes
	Motion detection (VMD)	yes	-	-	yes	yes
WJ-ND400K (V6.10) *14	MJPEG	yes	yes	yes	yes	yes
	MPEG4	-	yes	-	yes	-
	H.264	yes	yes	-	yes	yes
	H.265	-	-	-	-	-
	Audio *8	yes	yes	-	yes (ch1)	-
	PTZ	yes	yes *1	yes *1	yes	yes
	Motion detection (VMD)	yes	-	-	yes	yes
WJ-ND300A (V5.20) *4, *14 (Discontinued model)	MJPEG	[SC385]	yes	yes	yes	[GXE500 ch1]
	MPEG4	-	yes	-	yes	-
	H.264	[SC385]	yes	-	yes	[GXE500 ch1]
	H.265	-	-	-	-	-
	Audio	-	-	-	-	-
	PTZ	[SC385]	yes *1	yes *1	yes	[GXE500 ch1]
	Motion detection (VMD)	-	-	-	-	-
WJ-ND200 (V3.35) *4, *14 (Discontinued model)	MJPEG	[SC385]	yes	yes	yes	[GXE500 ch1]
	MPEG4	-	yes	-	yes	-
	H.264	[SC385]	yes	-	yes	[GXE500 ch1]
	H.265	-	-	-	-	-
	Audio *8 *11	[SC385]	yes	-	yes (ch1)	-
	PTZ	[SC385]	yes *1	yes *1	yes	[GXE500 ch1]
	Motion detection (VMD)	-	-	-	-	-

- [substitute model] : Register as a substitute model.
- \*1 : Only for remote PTZ cameras.
- \*2 : Support less than 1920x1080 ,including 1600x1200. 1920x1080 and 1600x1200 are not supported SD memory card backup and can be set the image quality:5-9 and the frame rate:upto 5fps.
- \*3 : Each recorder supports only wireline connection.
- \*4 : Displaying 16:9 is not supported on a NDR browser.
- \*7 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.
- \*8 : Supported G.726 and 32kbps.
- \*11 : This function is supported only when playing back.
- \*12 : Supported up to 30 fps
- \*13 : When using WV-SFV481/WV-SFN480 with WJ-NV200, recording stops for about 10 seconds at the time of a screen change in a main monitor.
- \*14 : Streams of H.264(3) and H.264(4) are not supported
- \*15 : When using over 6Mbps for bitrate, please use the "4K resolution" mode. SFV781L, SPV781L, SFV481, SFN480 support will be only 1-8ch.
- \*17 : The fish-eye dewarp function on the main monitor is supported.
- \*18 : The fish-eye dewarp function is supported by using the management software(WV-ASM200, WV-ASC970).
- \*19 : Supported maximum bitrate is 14Mbps.
- \*20 : 3rd stream and 4th stream of H.265 are supported, only when using H.265 cameras
- \*21 : Support less than 1280x720 for WV-X6511N
- \*22 : Transmission format must be switched from H.265(Factory default) to H.264 by connecting from web browser
- \*23 : Supported G.726/32kbps and AAC-LC/64kbps
- \*24 : Supported image capture sites are 4KUHD(3840x2160), WQHD(2560x1440), FHD(1920x1080) and HD(1280x720).

	Function	WV-X8570N/S8530N	WV-X6533LN/S6522LN	WV-X6531N/X6531NS X6511N	WV-S6530N	WV-S6131/S6111/S6130	WV-X4171/X4571L/X4571LM	WV-X4170	WV-S4550L/S4550LM	WV-S4150	WV-S1132/S1131	WV-S1550L	WV-S1531LN/S1531LTN S1531LNS	WV-S2131L/ S2131/S2130	WV-S2231
WV-ASM300 (V2.00)	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	H.265	yes	yes	yes	yes	-	yes	yes	yes	yes	yes	yes	yes	yes	yes
	Audio*23	yes	yes	yes	yes	yes	yes	-	yes	yes	yes	yes	yes	yes	yes
	PTZ	-	yes	yes	yes	yes	yes	-	yes	yes	yes	yes	yes	yes	yes
WV-ASM200 (V5.10) *24	MJPEG	yes	-	yes	yes	yes	-	yes	Unverified	Unverified	yes	-	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	Unverified	Unverified	-	-	-	-	-
	H.264	-	-	yes	yes	yes	-	-	Unverified	Unverified	yes	-	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio*8	-	-	yes	yes	yes	-	-	Unverified	Unverified	yes	-	yes	yes	yes
	PTZ	-	-	yes	yes	yes	-	-	Unverified	Unverified	yes	-	yes	yes	yes
WV-ASM100 (Ver8.00) *5, *14, *24	MJPEG	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio*8	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	-
WV-ASC970 (Ver19.00)	MJPEG	-	-	yes	Unverified	Unverified	-	-	Unverified	Unverified	yes	-	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	-	-	yes	Unverified	Unverified	-	-	Unverified	Unverified	yes	-	yes	yes	yes
	H.265	-	-	yes	Unverified	Unverified	-	-	Unverified	Unverified	yes	-	yes	yes	yes
	Audio*8	-	-	yes	Unverified	Unverified	-	-	Unverified	Unverified	yes	-	yes	yes	yes
	PTZ	-	-	-	-	-	-	-	Unverified	Unverified	-	-	-	-	-
WJ-GXD400 (Ver2.21) *6, *14, *20	MJPEG	-	-	yes	Unverified	Unverified	-	-	Unverified	Unverified	yes	-	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	-	-	yes	yes	yes	-	-	-	-	yes	-	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio*9	-	-	yes	yes	yes	-	-	-	-	yes	-	yes	yes	yes
	PTZ	-	-	yes	-	-	-	-	-	-	-	-	-	-	-
BB-HNP17 (Ver4.05)	MJPEG	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio*8	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	-

Discontinued model might have the function which doesn't work.  
 \*1 : Only for remote PTZ cameras.  
 \*5 : WV-ASM100 does not support displaying 16:9.  
 \*6 : Supported resolutions of WJ-GXD400 are only 1280x960, VGA and QVGA. Supported maximum bitrate is 8Mbps.  
 \*7 : Support functions are different depending on the "image capture mode". For details on "image capture mode", please refer to the operating instructions.  
 \*8 : Supported G.726.  
 \*9 : Supported G.726 as an Audio and MPEG4/H.264 as a Video.  
 \*14 : Streams of H.264(3) and H.264(4) are not supported.  
 \*16 : When displaying H.264 streaming of 2992x2992 resolution, please use a 64 bit OS and 4GB or more memory.  
 \*19 : Supported maximum bitrate is 14Mbps.  
 \*20 : Supported maximum bitrate is 8Mbps. Supported maximum resolution is 1280x960.  
 \*21 : WV-ASM200 does not support wiper function.  
 \*22 : Rain/Flick button can use, only when the capture mode is cropping of H.264 stream. Zoom button cannot use.  
 \*23 : Supported G.726 or AAC.  
 \*24 : Please connect to the camera from the PC browser and change the authentication method from Digest to Digest or Basic.  
**\*25 : Video display may take some time depending on the frame rate used. Also, depending on the camera model, video may be delayed.**

	Function	WV-S2550L/S2250L	WV-S2531LN/S2531LTN	WV-S3131L/S3111L	WV-S3531L/S3511L	WV-S3532LM/S3512LM	WV-S2570L/S2270L S1570L	WV-SPV781L/SPV781L	WV-SUD638	WV-SPN611/SPN631	WV-SPW631LT/SPW631L	WV-SFN611L/SFN631L/SFR611L/SFR631L/SFV611L/SFV631L/SFV631LT	WV-SPW611L/SPW611	WV-SPN531	WV-SPN531A
WV-ASM300 (V2.00)	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes *18	yes	yes	yes	yes	yes	yes	yes
	H.265	yes	yes	yes	yes	yes	yes	-	-	-	-	-	-	-	-
	Audio *23	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
Direct connection to camera	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	RTP over HTTP	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MJPEG	-	yes	-	-	-	-	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	-	yes	-	-	-	-	yes *18	-	yes	yes	yes	yes	yes	yes
WV-ASM200 (V5.10) *24	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *8	-	yes	-	-	-	-	yes	yes	yes	yes	yes	yes	yes	yes
	PTZ	-	yes	-	-	-	-	-	yes	-	-	-	-	-	-
	RTP over HTTP	-	yes	-	-	-	-	yes	yes	yes	yes	yes	yes	yes	yes
	MJPEG	-	-	-	-	-	-	yes	yes	yes	yes	yes	yes	yes	yes
WV-ASM100 (Ver8.00) *5, *14, *24	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	-	-	-	-	-	-	yes	yes	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *8	-	-	-	-	-	-	yes	yes	yes	yes	yes	yes	yes	yes
	PTZ	-	-	-	-	-	-	-	yes *21	-	-	-	-	-	-
Direct connection to camera (Discontinued model)	RTP over HTTP	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	MJPEG	-	yes	-	-	-	-	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	-	yes	-	-	-	-	yes *19	yes	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
WV-ASC970 (Ver19.00)	Audio *8	-	yes	-	-	-	-	yes	yes	yes	yes	yes	yes	yes	yes
	PTZ	-	-	-	-	-	-	-	yes	yes	yes	yes	yes	yes	yes
	RTP over HTTP	-	yes	-	-	-	-	yes	yes	yes	yes	yes	yes	yes	yes
	MJPEG	-	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	-
WJ-GXD400 (Ver2.21) *6, *14, *20	H.264	-	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *9	-	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	RTP over HTTP	-	-	-	-	-	-	-	-	-	-	-	-	-	-
BB-HNP17 (Ver4.05)	MJPEG	-	-	-	-	-	-	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264 *25	-	-	-	-	-	-	yes	yes	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *8	-	-	-	-	-	-	yes	yes	yes	yes	yes	yes	yes	yes
Direct connection to camera	PTZ	-	-	-	-	-	-	yes *22	yes	-	-	-	-	-	-
	RTP over HTTP	-	-	-	-	-	-	yes	yes	yes	yes	yes	yes	yes	yes

Discontinued model might have the function which doesn't work.  
 \*1 : Only for remote PTZ cameras.  
 \*5 : WV-ASM100 does not support displaying 16:9.  
 \*6 : Supported resolutions of WJ-GXD400 are only 1280x960, VGA and QVGA. Supported maximum bitrate is 8Mbps.  
 \*7 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.  
 \*8 : Supported G.726.  
 \*9 : Supported G.726 as an Audio and MPEG4/H.264 as a Video.  
 \*14 : Streams of H.264(3) and H.264(4) are not supported.  
 \*16 : When displaying H.264 streaming of 2992x2992 resolution, please use a 64 bit OS and 4GB or more memory.  
 \*19 : Supported maximum bitrate is 14Mbps.  
 \*20 : Supported maximum bitrate is 8Mbps. Supported maximum resolution is 1280x960.  
 \*21 : WV-ASM200 does not support wiper function.  
 \*22 : Rain/Flick button can use, only when the capture mode is cropping of H.264 stream. Zoom button cannot use.  
 \*23 : Supported G.726 or AAC.  
 \*24 : Please connect to the camera from the PC browser and change the authentication method from Digest to Digest or Basic.  
 \*25 : Video display may take some time depending on the frame rate used. Also, depending on the camera model, video may be delayed.

	Function	WV-SPW532L	WV-SPW531AL	WV-SFN531/SFR531/SFV531	WV-SW598/SW598A/SC588/SC588A	WV-SW559/SF549/SF539/SP509	WV-SW558/SF548/SF538/SP508	WV-NW5025/NP502	WV-SFV481/SFN480	WV-SW458/SW458MA/SF438/SF48E	WV-S1112/S1111	WV-S1511LN	WV-S2111U/S2111O	WV-S2211	WV-S2511LN
WV-ASM300 (V2.00)	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	yes	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	yes *17, *18	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	yes	yes	yes	yes	yes
	Audio *23	-	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
Direct connection to camera	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	RTP over HTTP	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	yes	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	yes *17, *18	yes	yes	yes	yes	yes	yes
WV-ASM200 (V5.10) *24	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *8	-	yes	yes	-	yes	-	yes	yes	yes	yes	yes	yes	yes	yes
	PTZ	-	-	-	-	-	-	-	-	yes	-	-	-	-	-
	RTP over HTTP	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	-	-	-	-	-	-
WV-ASM100 (Ver8.00) *5, *14, *21	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	-	-	-	-	-	-	-
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *8	-	yes	yes	yes	yes	-	-	-	-	-	-	-	-	-
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	-
Direct connection to camera (Discontinued model)	RTP over HTTP	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	yes *17, *19	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	yes	yes	yes	yes	yes
WV-ASC970 (Ver19.00)	Audio *8	-	yes	yes	yes	yes	-	yes	yes	yes	yes	yes	yes	yes	yes
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	RTP over HTTP	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	-
WJ-GXD400 (Ver2.21) *6, *14, *20	H.264	yes	yes	yes	yes	yes	yes	yes	-	-	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *9	-	yes	yes	yes	yes	-	yes	-	-	yes	yes	yes	yes	yes
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	RTP over HTTP	-	-	-	-	-	-	-	-	-	-	-	-	-	-
BB-HNP17 (Ver4.05)	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	H.264 *15	yes	yes	yes	yes	yes	yes	yes	yes *16	yes	-	-	-	-	-
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *8	-	yes	yes	yes	yes	-	yes	yes	yes	-	-	-	-	-
PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	-	
RTP over HTTP	yes	yes	yes	yes	yes	yes	yes	yes	yes	-	-	-	-	-	

Discontinued model might have the function which doesn't work.  
 \*1 : Only for remote PTZ cameras.  
 \*5 : WV-ASM100 does not support displaying 16:9.  
 \*6 : Supported resolutions of WJ-GXD400 are only 1280x960, VGA and QVGA. Supported maximum bitrate is 8Mbps.  
 \*7 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.  
 \*8 : Supported G.726.  
 \*9 : Supported G.726 as an Audio and MPEG4/H.264 as a Video.  
 \*14 : Streams of H.264 (3) and H.264 (4) are not supported.  
 \*16 : When displaying H.264 streaming of 2992x2992 resolution, please use a 64 bit OS and 4GB or more memory.  
 \*19 : Supported maximum bitrate is 14Mbps.  
 \*20 : Supported maximum bitrate is 8Mbps. Supported maximum resolution is 1280x960.  
 \*21 : WV-ASM200 does not support wiper function.  
 \*22 : Pan/Tilt button can use, only when the capture mode is cropping of H.264 stream. Zoom button cannot use.  
 \*23 : Supported G.726 or AAC.  
 \*24 : Please connect to the camera from the PC browser and change the authentication method from Digest or Digest or Basic.  
**\*25 : Video display may take some time depending on the frame rate used. Also, depending on the camera model, video may be delayed.**

	Function	WV-SPN310/SPN311/SPW311LH	WV-SPN310A/SPN311A	WV-SPW312L	WV-SPW311AL	WV-SPN311/SFN310/SFN311L/SFR311/SFR310/SFV311/SFV310	WV-SFN311A/SFN310A/SFR311A/SFR310A/SFV311A/SFV310A	WV-SW397/SW397A/SW397B/SC387/SC387A	WV-SW396/SW395/SC386/SC385/SC384	WV-SW355/SW352/SF346/SF342	WV-SF330 series/SP300 series	WV-SW316L/SW316	WV-SW314	WV-SFV130(M)/SFV110(M)	WV-SFN130/SFN110
WV-ASM300 (V2.00)	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	yes	yes	yes	yes	yes	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *8	yes	yes	-	-	yes	yes	yes	yes	yes	yes	yes	-	-	yes
	PTZ	-	-	-	-	-	-	-	-	-	yes	-	-	-	-
Direct connection	RTP over HTTP	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	yes	yes	yes	yes	yes	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *8	yes	yes	-	-	yes	yes	yes	yes	yes	yes	yes	-	-	yes
WV-ASM200 (V5.10) *24	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	RTP over HTTP	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	yes	yes	yes	yes	yes	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
Direct connection to camera	Audio *8	yes	yes	-	-	yes	yes	yes	yes	yes	yes	yes	-	-	yes
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	RTP over HTTP	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	yes	yes	yes	yes	yes	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
WV-ASM100 (Ver8.00) *5, *14, *21	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *8	yes	yes	-	-	yes	yes	yes	yes	yes	yes	yes	-	-	yes
	PTZ	-	-	-	-	-	-	-	yes	yes	-	-	-	-	-
	RTP over HTTP	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	yes	yes	yes	yes	yes	-	-
Direct connection to camera (Discontinued model)	H.264	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *8	yes	yes	-	-	yes	yes	yes	yes	yes	yes	yes	-	-	yes
	PTZ	-	-	-	-	-	-	-	yes	yes	-	-	-	-	-
	RTP over HTTP	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
WV-ASC970 (Ver19.00)	MPEG4	-	-	-	-	-	-	-	yes	yes	yes	yes	yes	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *8	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	-	-	yes
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	RTP over HTTP	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
WJ-GXD400 (Ver2.21) *6, *14, *20	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	yes	yes	yes	yes	yes	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *9	yes	yes	-	yes	yes	yes	yes	yes	yes	yes	yes	-	yes	yes
	PTZ	-	-	-	-	-	-	-	-	-	-	-	-	-	-
BB-HNP17 (Ver4.05)	RTP over HTTP	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	MJPEG	-	-	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	yes	yes	yes	yes	yes	-	-
	H.264 *25	-	-	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-	-	-	-	-	-
	Audio *8	-	-	-	yes	yes	yes	yes	yes	yes	yes	yes	-	yes	yes
PTZ	-	-	-	-	-	-	-	yes	yes	-	-	-	-	-	
RTP over HTTP	-	-	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	

Discontinued model might have the function which doesn't work.  
 \*1 : Only for remote PTZ cameras.  
 \*5 : WV-ASM100 does not support displaying 16:9.  
 \*6 : Supported resolutions of WJ-GXD400 are only 1280x960, VGA and QVGA. Supported maximum bitrate is 8Mbps.  
 \*7 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.  
 \*8 : Supported G.726.  
 \*9 : Supported G.726 as an Audio and MPEG4/H.264 as a Video.  
 \*14 : Streams of H.264(3) and H.264(4) are not supported.  
 \*16 : When displaying H.264 streaming of 2992x2992 resolution, please use a 64 bit OS and 4GB or more memory.  
 \*19 : Supported maximum bitrate is 14Mbps.  
 \*20 : Supported maximum bitrate is 8Mbps. Supported maximum resolution is 1280x960.  
 \*21 : WV-ASM200 does not support wiper function.  
 \*22 : Pan/Tilt button can use, only when the capture mode is cropping of H.264 stream. Zoom button cannot use.  
 \*23 : Supported G.726 or AAC.  
 \*24 : Please connect to the camera from the PC browser and change the authentication method from Digest to Digest or Basic.  
**\*25 : Video display may take some time depending on the frame rate used. Also, depending on the camera model, video may be delayed.**

	Function	WV-SW158/SP138	WV-SW155/SW155MA/SW152/SFA35/SP132/SW115	WV-SP105/SP102	WV-SW175/SW172/ST165/ST162	WV-SW174W	BB-HCM7 series	BB-HCM5 series	WJ-GXE500	WJ-GXE100
WV-ASM300 (V2.00)	MJPEG	yes	yes	yes	yes	yes	-	-	yes	yes
	MPEG4	-	-	-	-	-	-	-	yes	-
	H.264	yes	yes	yes	yes	yes	-	-	yes	yes
	H.265	-	-	-	-	-	-	-	-	-
	Audio*8	yes	-	-	-	yes	-	-	yes (ch1)	-
	PTZ	-	-	-	-	yes	-	-	-	-
Direct connection	RTP over HTTP	yes	yes	yes	yes	yes	-	-	yes	yes
	MJPEG	yes	yes	yes	yes	yes	-	-	yes	yes
	MPEG4	-	-	-	-	-	-	-	yes	-
	H.264	yes	yes	yes	yes	yes	-	-	yes	yes
	H.265	-	-	-	-	-	-	-	-	-
	Audio*8	yes	-	-	-	yes	-	-	yes (ch1)	-
WV-ASM200 (V5.10) *24	PTZ	-	-	-	-	yes	-	-	-	-
	RTP over HTTP	yes	yes	yes	yes	yes	-	-	yes	yes
	MJPEG	yes	yes	yes	yes	yes	-	-	yes	yes
	MPEG4	-	-	-	-	-	-	-	yes	-
	H.264	yes	yes	yes	yes	yes	-	-	yes	yes
	H.265	-	-	-	-	-	-	-	-	-
Direct connection to camera	Audio*8	yes	-	-	-	yes	-	-	yes (ch1)	-
	PTZ	-	-	-	-	yes	-	-	-	-
	RTP over HTTP	yes	yes	yes	yes	yes	-	-	yes	yes
	MJPEG	yes	yes	yes	yes	yes	-	-	yes	-
	MPEG4	-	-	-	-	-	-	-	yes	-
	H.264	yes	yes	yes	yes	yes	-	-	yes	yes
WV-ASH100 (Ver8.00) *5, *14, *24	H.265	-	-	-	-	-	-	-	-	-
	Audio*8	yes	-	-	-	yes	-	-	yes (ch1)	-
	PTZ	-	-	-	-	yes	-	-	yes	-
	RTP over HTTP	yes	yes	yes	yes	yes	-	-	-	-
	MJPEG	yes	yes	yes	yes	yes	-	-	yes	yes
	MPEG4	-	-	-	-	-	-	-	yes	-
Direct connection to camera (Discontinued model)	H.264	yes	yes	yes	yes	yes	-	-	yes	yes
	H.265	-	-	-	-	-	-	-	-	-
	Audio*8	yes	-	-	-	yes	-	-	yes (ch1)	-
	PTZ	-	-	-	-	yes	-	-	-	-
	RTP over HTTP	yes	yes	yes	yes	yes	-	-	yes	yes
	MJPEG	yes	yes	yes	yes	yes	-	-	yes	yes
WV-ASC970 (Ver19.00)	MPEG4	-	-	-	-	-	-	-	yes	-
	H.264	yes	yes	yes	yes	yes	-	-	yes	yes
	H.265	-	-	-	-	-	-	-	-	-
	Audio*8	yes	-	-	-	yes	-	-	yes (ch1)	-
	PTZ	-	-	-	-	yes	-	-	-	-
	RTP over HTTP	yes	yes	yes	yes	yes	-	-	yes	yes
WJ-GXD400 (Ver2.21) *6, *14, *20	MJPEG	yes	yes	yes	yes	yes	-	-	yes	yes
	MPEG4	-	-	-	-	-	-	-	yes	yes
	H.264	yes	yes	yes	yes	yes	-	-	yes	yes
	H.265	-	-	-	-	-	-	-	-	-
	Audio*9	yes	-	-	-	yes	-	-	yes (ch1)	-
	PTZ	-	-	-	-	yes	-	-	-	-
BB-HNP17 (Ver4.05)	RTP over HTTP	yes	yes	yes	yes	yes	-	-	yes	yes
	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	yes	yes	yes	-
	H.264 *25	yes	yes	yes	yes	yes	yes	yes	yes	yes
	H.265	-	-	-	-	-	-	-	-	-
	Audio*8	yes	-	-	-	yes	yes	yes	yes (ch1)	-
PTZ	-	-	-	-	yes	yes	yes *1	yes *1	yes	
RTP over HTTP	yes	yes	yes	yes	yes	-	-	yes	yes	

Discontinued model might have the function which doesn't work.  
 \*1 : Only for remote PTZ cameras.  
 \*5 : WV-ASM100 does not support displaying 16:9.  
 \*6 : Supported resolutions of WJ-GXD400 are only 1280x960, VGA and QVGA. Supported maximum bitrate is 8Mbps.  
 \*7 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.  
 \*8 : Supported G.726.  
 \*9 : Supported G.726 as an Audio and MPEG4/H.264 as a Video.  
 \*14 : Streams of H.264(3) and H.264(4) are not supported.  
 \*16 : When displaying H.264 streaming of 2992x2992 resolution, please use a 64 bit OS and 4GB or more memory.  
 \*19 : Supported maximum bitrate is 14Mbps.  
 \*20 : Supported maximum bitrate is 8Mbps. Supported maximum resolution is 1280x960.  
 \*21 : WV-ASM200 does not support wiper function.  
 \*22 : Rain/Ink button can use, only when the capture mode is cropping of H.264 stream. Zoom button cannot use.  
 \*23 : Supported G.726 or AAC.  
 \*24 : Please connect to the camera from the PC browser and change the authentication method from Digest or Digest or Basic.  
**\*25 : Video display may take some time depending on the frame rate used. Also, depending on the camera model, video may be delayed.**

	Function	WJ-NX400	WJ-NX300	WJ-NX200	WJ-NV300	WJ-NV200	WJ-ND400K	WJ-ND300A	WJ-ND200 (Discontinued model)	WJ- HD616/HD716	WJ-HD300 (Discontinued model)
WV-ASM300 (V1.30)	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes	-	-
	MPEG4	-	-	-	-	yes	yes	yes	yes	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	yes	yes	-
	H.265	yes	yes	yes	-	-	-	-	-	-	-
	Original	-	-	-	-	-	-	-	-	-	yes
	Audio*10	Live/Playback(Receive)	Live/Playback(Receive)	Live/Playback(Receive)	Live/Playback(Receive)	Live/Playback(Receive)	Live/Playback(Receive)	-	Playback(Receive)	Live/Playback(Receive)	-
	PTZ	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
Via Recorder	VMD	yes	yes	yes	yes	yes	yes	-	-	yes	-
	RTP over HTTP	yes	yes	yes	yes	yes	-	-	-	yes	-
	MJPEG	-	-	-	yes	yes	yes	yes	yes	-	-
	MPEG4	-	-	-	-	yes	yes	yes	yes	-	-
	H.264	-	-	-	yes	yes	yes	yes	yes	yes	-
	H.265	-	-	-	-	-	-	-	-	-	-
	Original	-	-	-	-	-	-	-	-	-	yes
WV-ASM200 (V5.10)	Audio*8	-	-	-	Live/Playback(Receive)	Live/Playback(Receive)	Live/Playback(Receive)	-	Playback(Receive)	Live/Playback(Receive)	-
	PTZ	-	-	-	yes	yes	yes	yes	yes	yes	yes
	VMD	-	-	-	yes	yes	yes	-	-	yes	-
	RTP over HTTP	-	-	-	yes	yes	yes	-	-	yes	-
	MJPEG	-	-	-	-	yes	yes	yes	yes	-	-
	MPEG4	-	-	-	-	yes	yes	yes	yes	-	-
	H.264	-	-	-	-	yes	yes	yes	yes	yes	-
WV-ASM100 (Ver8.00)	H.265	-	-	-	-	yes	yes	yes	yes	yes	-
	Original	-	-	-	-	-	-	-	-	-	-
	Audio*8	-	-	-	-	Live/Playback(Receive)	Live/Playback(Receive)	-	Playback(Receive)	Live/Playback(Receive)	yes
	PTZ	-	-	-	-	yes	yes	yes	yes	yes	yes
	VMD	-	-	-	-	yes	yes	-	-	yes	-
	RTP over HTTP	-	-	-	-	yes	yes	-	-	yes	-
	WV-ASM970 (Ver19.00)	MJPEG	yes	-	-	yes	yes	yes	yes (Playback only)	yes (Playback only)	-
MPEG4	-	-	-	-	yes	yes	yes	yes (Playback only)	yes (Playback only)	-	-
H.264	yes	-	-	yes	yes	yes	yes (Playback only)	yes (Playback only)	yes	-	
H.265	-	-	-	-	-	-	-	-	-	-	
Original	-	-	-	-	-	-	-	-	-	yes	
Audio*8	Live/Playback(Receive)	-	-	-	Live/Playback(Receive)	Playback(Receive)	Playback(Receive)	-	Playback(Receive)	Playback(Receive)	-
PTZ	yes	-	-	yes	yes	yes	-	-	yes	yes	
VMD	yes	-	-	yes	yes	yes	-	-	yes	-	
RTP over HTTP	yes	-	-	yes	yes	yes	-	-	yes	-	
WJ-GXD400 (Ver2.21) *6	MJPEG	-	-	-	-	-	yes	yes (Playback only)	yes (Playback only)	-	-
	MPEG4	-	-	-	-	-	yes	yes (Playback only)	yes (Playback only)	-	-
	H.264	-	-	-	-	-	yes	yes (Playback only)	yes (Playback only)	yes	-
	H.265	-	-	-	-	-	-	-	-	-	-
	Original	-	-	-	-	-	-	-	-	-	yes
	Audio*9	-	-	-	-	-	Playback(Receive)	-	Playback(Receive)	Playback(Receive)	-
	PTZ	-	-	-	-	-	yes	-	-	yes	yes
VMD	-	-	-	-	-	yes	-	-	yes	-	
RTP over HTTP	-	-	-	-	-	-	-	-	-	-	

Discontinued model might have the function which doesn't work.  
 \*6 : Supported resolutions of WJ-GXD400 are only 1280x960, VGA and QVGA. Supported maximum bitrate is 8Mbps  
 \*8 : Supported only G.726.  
 \*9 : Supported G.726 as an Audio and MPEG4/H.264 as a Video.  
 \*10 : Supported G.726 or AAC.